

## Russell Stoll Connectors

Part Number	Receptacle	Service			Breaker		Wire		Conduit Inches
		Volts	AMP	Phase	P	A	Qty.	Size	
IBM A	RS 3913	208	20	1	2	20	3	12 AWG	0.5
IBM A-U1	RS 3913-U1	120	20	1	1	20	3	12 AWG	0.5
IBM A-U2	RS 3913-U2	208	15	1	2	15	3	12 AWG	0.5
IBM B	RS 3914	208	15	3	3	15	4	12 AWG	0.5
IBM C	RS 3933	208	30	1	2	30	3	10 AWG	0.5
IBM D	RS 3934	208	30	3	3	30	4	10 AWG	0.5
IBM E	RS 7428	208	60	3	3	60	4	6 AWG	0.75
IBM F	RS JCS1034H	208	100	3	3	100	4	3 AWG	1.25